

TYPE B & C FISCALIZATION

- Connect the device to the pc/laptop via USB Cable
- Check the COM port connected in the device manager
- Open the FPCMDKE Application
- Select the correct COM Port on the FPCMDke and Enter the Baud Rate: 115200
- Click on connect

Connection

USB / Serial COM Port: COM3 Find

TCP / WiFi Baud Rate: 115200 Connect

Receipts Reports Service Network Settings Reg CU Log CU

Open Fiscal Sales Receipt

Trader System Invoice Number

Format Brief Open Fiscal Receipt

Open Invoice Receipt

Invoice Type

Company Name

Client PIN Number

Headquarters

Address

Postal code and City

Exemption Number

Trader System Invoice Number

Related Invoice Number

Open Receipt

Sell Article

Article Name*

Price*

HS Code*

HS Name

VAT Class*

VAT Class Rate*

Measure Unit*

Quantity*

Discount / Addition in %

* - required field

Sell Article

Subtotal

STL

In %

Disc / Add

Subtotal

Read information about current opened receipt

Subtotal VAT A

Subtotal VAT B

Subtotal VAT C

Subtotal VAT D

Subtotal VAT E

Receipt actions

Close Fiscal Receipt

Cancel Fiscal Receipt

Receipt Duplicate

Connected: KRAMW008201909000328

- Open the Network Tab and click on Load

Connection

USB / Serial IP: 172.16.0.38

TCP / WiFi Password: Password Connect

Receipts Reports Service Network Settings Reg CU Log CU

Load Save all

Network Settings

DHCP Client:

IP:

Netmask:

DNS:

Gateway:

MAC Address

GPRS Settings

GPRS APN:

GPRS username:

GPRS password:

Authentication type: None

Module Tests

Start GPRS Test

Start WiFi Test

Start LAN Test

WiFi

Scan and Print Wireless networks

Network name (SSID)

Network password

ZFP Settings

Enable ZFP over LAN/WIFI

LAN/WiFi Password

TCP Idle timeout

Device Usage

LAN WiFi

Server Settings

Communication module: GSM LAN/WiFi

Address

Invoice threshold

Time threshold

NTP Address

Connected: KRAMW008201909000328

- Enter the network SSID and the Password if you are using WIFI
 - Enable the ZFP over LAN/WIFI and Enter the password as Password.
 - Select the connection as WIFI or LAN
 - To set the IP Address as Static disable the DHCP Client check box
 - Enter the IP address, Netmask, DNS and the Default Gateway
- Note:** To use the GPRS option use the below configurations.

Safaricom Line

- GPRS APN:** Safaricom
- GPRS Username:** saf
- GPRS Password: data

Airtel Line

- GPRS APN:** airtelgprs.com
- GPRS Username:** Airtel
- GPRS Password:

- Click on the REG TAB
- On the FD Number Click on Read to view the Serial Number of the device.

FPcmdKE

Connection

USB / Serial IP: 172.16.0.38

TCP / WiFi Password: Password

Receipts Reports Service Network Settings Reg CU Log CU

FD Number

Serial N°: KRAMW008201909000328

Password:

Fiscalisation

PIN Number: P051140749R

Password: 23KTR9

Connected: KRAMW008201909000328

- On the Fiscalisation, enter the Correct PIN for the client/device owner.
- Enter the Password: 23KTR9
- Click on SAVE.
- Click on Fiscalize to activate/handshake the device.
- Make the first transaction.